

REMARKS

Claims 1-15 are all the claims pending in the present application. Applicant thanks the Examiner for indicating that claims 10, 11, 13, and 14 are allowed. Also, Applicant thanks the Examiner for withdrawing the previous prior art rejections. However, the Examiner now adds a new reference to support the rejections of claims 1-9, 12, and 15. Specifically, claims 1-9, 12 and 15 are rejected under 35 U.S.C. § 102(e) as being anticipated by Lee et al. (2004/0027482).

To overcome this rejection, Applicant perfects priority under 35 U.S.C. § 119, and requests removal of Lee as a prior art reference. Lee has a filing date of April 14, 2003, which is after the filing date of KPA 10-2002-0071667 (November 18, 2002), from which the present application claims benefit of priority. Applicant submits herewith a verified English language translation of priority document KPA 10-2002-0071667, and a statement that the translation is accurate.

In view of the above, reconsideration and allowance of this application are now believed to be in order, and such actions are hereby solicited. If any points remain in issue which the Examiner feels may be best resolved through a personal or telephone interview, the Examiner is kindly requested to contact the undersigned at the telephone number listed below.

The USPTO is directed and authorized to charge all required fees, except for the Issue Fee and the Publication Fee, to Deposit Account No. 19-4880. Please also credit any overpayments to said Deposit Account.

Respectfully submitted,


SUGHRUE MION, PLLC
Telephone: (202) 293-7060
Facsimile: (202) 293-7860

WASHINGTON OFFICE

23373

CUSTOMER NUMBER

Date: April 10, 2008


Diallo T. Crenshaw
Registration No. 52,778


DECLARATION

I, Meeseon Lee, a Korean citizen of 502-816, Bang-hwa Apartment, Bangwha-dong, Gangsu-gu, Seoul, Korea do hereby solemnly and sincerely declare as follows:

1. That I am well acquainted with the English and Korean languages.
2. That the following is a correct translation into English of Korean Patent

Application No. 2002-0071667 filed November 18, 2002, and I make the solemn declaration conscientiously believing the same to be true.

Seoul, April 1, 2008



Meeseon Lee

[DOCUMENT] Application for Patent

[CLASSIFICATION OF RIGHTS] Patent

[RECEIVING PERSON] The commissioner

[DATE OF FILING] NOVEMBER 18, 2002

5 [TITLE OF THE INVENTION-KOREAN] 화면분할 기능을 갖는 영상디스플레이
장치

[TITLE OF THE INVENTION-ENGLISH] Image displayer with separating screen
function

[APPLICANT]

10 [NAME] Samsung Electronics Co., Ltd.

[APPLICANT CODE] I-1998-104271-3

[AGENT]

[NAME] Hong-sik JEONG

[ATTORNEY CODE] 9-1998-000543-3

15 [GENERAL POWER OF ATTORNEY NO.] 2000-046970-1

[INVENTOR]

[NAME-KOREAN] 고흥일

[NAME-ENGLISH] KOH, HYUNG IL

[RESIDENT REGISTRATION NUMBER] 690423-1110021

20 [ZIP CODE] 440-710

[ADDRESS] 104-1404, Cheoncheon Raemian Apt., Cheoncheon-dong, Jangan-gu,
Suwon-si, Gyeonggi-do, Korea

[NATIONALITY] KR

[EXAMINATION REQUEST] YES

25 [PURPOSE] I, hereby, submit the present application for the Patent and request the
examination of the present invention under the Article 42 and the Article 60 of the Patent Law.

Attorney

Hong-sik JEONG (seal affixed)

[Official Fee]

[Basic fee] 20 page ₩29,000

30 [Additional fee] 4 pages ₩4,000

[Claiming Priority Right] 0 case ₩0

[Filing Request For Examination]	11 claims	₩461,000
[Total]		₩494,000
[Documents]	1. One copy of Abstract, Specification (& drawings)	

[ABSTRACT OF THE DISCLOSURE]

[Abstract]

An image displayer of a multi-screen system, which is comprised of at least two image displayers. The image displayer comprises a screen, a video decoder for performing
5 an analog-to-digital conversion with respect to a video input signal, and a scaler for selecting a video signal corresponding to a predetermined area of the screen from video signals
outputted from the video decoder by an externally transmitted control signal, and enlarging
the selected video signal according to a size of the screen. Accordingly, the image displayer
does not require an extra signal separator when constituting a multi-vision system and is not
10 limited in number. Also, the image displayer can be used to receive a general broadcasting
channel when it is not in use for the multi-vision system.

[The main figure]

Fig. 2

[Search term]

15 multi-vision system, scaler, signal separator, multi-screen

[SPECIFICATION]

[The title of the invention]

Image displayer with separating screen function

[The brief description of the drawings]

5 Fig. 1 is a block diagram showing a multi-screen system using a conventional video signal separator;

Fig. 2 is a block diagram showing an image displayer having a screen control function according to a preferred first embodiment of the present invention;

10 Figs. 3a and 3b are views for explaining the operations of the set value storing unit and a frame buffer controlling unit of Fig. 2;

Fig. 4 is a block diagram according to a second preferred embodiment of the present invention;

Figs. 5a and 5b are views showing output waves of the first counter and the exclusive OR gate of a logic device of Fig. 4; and

15 Fig. 6 is a view showing an example of an OSD window for the setting of the image displayer.

Description of the reference numerals in the drawings

110 : video decoder	120 : deinterlacer
130 : scaler	140 : PDP panel
20 150 : OSD unit	160 : control unit

[Detailed description of the invention]

[Object of the invention]

[The field of the invention and the related art]

25 The present invention relates to an image displayer, and more particularly, to an image displayer which performs a multi-screen function without requiring an extra video signal separator.

Image displayers such as a television set and a PDP (Plasma Display Panel) have a screen varying in size from 30 inch to 60 inch, and are generally used at home. The size of such an image displayer limits the place of its use, and accordingly it is difficult to use it for
30 the purposes such as advertisement and election campaign. In order to overcome this drawback, a video signal separator is used, for allowing a single image to be displayed on a plurality of connected image displayers. Generally, the video signal separator properly

distributes a single video signal to the plurality of image displayers to thus have a single image displayed on a large screen.

Fig. 1 is a block diagram showing a multi-screen system using a conventional video signal separator.

5 The multi-screen system as shown in Fig. 1 has a video signal separator 10 and a plurality of image displayers 21-24 for displaying respectively assigned views according to the distributed signal.

10 The video signal separator 10 separates a video signal supplied from a video cassette recorder, a tuner, and other video sources to four (4) signals. The separated video signals are processed so that they can be displayed on the image displayers 21-24 in a single full-screen. In order to enlarge each video signal to a full-screen size, the video signal separator 10 has to have a corresponding function. Also, the multi-screen system has to have a processor to operate four (4) screens for 2 x 2 multi-screen system or sixteen (16) screens for 4 x 4 multi-screen system in a full-screen. Accordingly, the conventional multi-screen
15 system requires an expensive video signal separator 10 to realize the large sized screen. Furthermore, the large sized screen cannot be realized if output ports provided in the video signal separator 10 do not match with the plurality of image displayers in number.

[Technical object of the invention]

20 The present invention has been developed in order to solve the above problems in the related art. Accordingly, an aspect of the present invention provides an image displayer capable of realizing a large sized screen without requiring an extra signal separator and in unlimited number of screens.

[Construction and operation of the invention]

25 In order to achieve the above aspect and/or other features of the present invention, an image displayer of a multi-screen system comprised of at least two image displayers is provided. The image displayer comprises a screen, a video decoder for performing an analog-to-digital conversion with respect to an video input signal, and a scaler for selecting a video signal corresponding to a predetermined area of the screen from video signals outputted from the video decoder by an externally transmitted control signal, and enlarging the selected
30 video signal according to a size of the screen.

Preferably, the signal selecting unit comprises a frame buffer for being inputted with

the video signal outputted from the video decoder and storing the video signal for a predetermined time, and then outputting the video signal to the scaling unit, a set value storing unit for storing a set value for the multi-screen function, and a frame buffer control unit for selecting a predetermined area of the video signal of the video decoder stored in the frame buffer in response to one of the set values pre-set by the set value storing unit.

Preferably, the image displayer further comprises a control unit for selecting one of the plurality of set values stored in the set value storing unit in response to an externally transmitted control signal.

Preferably, the image displayer further comprises an OSD unit for displaying a predetermined font on the screen according to the control signal supplied from the control unit, and controlling the multi-screen function on an OSD window.

Preferably, the externally transmitted control signal is the one generated by a setting key attached to a remote controller and the image displayer.

Also, the above aspect is achieved by providing an image displayer comprising a video decoder for performing an analog-to-digital conversion with respect to a video input signal; a video signal selecting unit for selecting a video signal outputted from the video decoder to display in a predetermined area of a screen in response to an externally transmitted control signal; a frame buffer for receiving the video signal selected by the video signal selecting unit and re-ordering the video signal by the order of input, and a scaler for scaling the video signal re-arranged by the frame buffer.

Preferably, the video signal selecting unit comprises a first selecting unit for selecting a predetermined area of a video signal added to a horizontal sync signal of the video input signal converted from analog to digital by the video decoder, and a second selecting unit for selecting a predetermined area of a video signal added to a vertical sync signal of the video input signal converted from analog to digital by the video decoder.

The first selecting unit comprises a first initial value storing unit for storing a plurality of initial values for the selection of the predetermined area of the video signal outputted from the video decoder and added to the horizontal sync value, a first multiplexer for selecting one of the initial values stored in the first initial value storing unit in response to the externally transmitted control signal, a first counter for generating a pulse of a predetermined period based on the initial value selected by the first multiplexer; and a first exclusive OR gate for performing a masking with respect to the video signal outputted from the video decoder using

the pulse outputted from the first counter and outputting only a desired area of the video signal.

Preferably, the second selecting unit comprises a second initial value storing unit for storing a plurality of initial values for the selection of the predetermined area of the video
5 signal outputted from the video decoder and added to the vertical sync signal, a second multiplexer for selecting any one value of the initial values stored in the second initial value storing unit in response to the control signal from the external device, a second counter for generating a pulse of a predetermined period according to the initial value selected by the
10 second multiplexer; and a second exclusive OR gate for performing a masking with respect to the video signal outputted from the video decoder, using the pulse output from the second counter, thereby outputting only a desired area of the vide signal.

Preferably, the image displayer further comprises an OSD unit for displaying a predetermined font on the screen in response to the externally transmitted control signal so that the multi-screen function can be controlled on the OSD.

15 Hereinbelow, exemplary embodiments of the present invention will be explained in detail with reference to drawings.

Fig. 2 is a block diagram showing an image displayer having a screen control function according to a first preferred embodiment of the preset invention.

The image displayer as shown in Fig. 2 includes a video decoder 110, a deinterlacer
20 120, a scaler 130, a PDP panel 140, an OSD unit 150, and a control unit 160.

The video decoder 110 performs an analog-to-digital conversion with respect to video signals supplied from a broadcasting station, a video cassette recorder, and other video sources.

25 The deinterlacer 120 converts the video signals digitalized by the video decoder 110 in a progressive method.

The scaler 130 converts the digital video signal, which is converted in the progressive method and outputted from the deinterlacer 120, in accordance with a resolution of the PDP panel 140. Also, the scaler 130 is controlled by the control unit 160 in response to a control
30 signal generated from an external device such as a remote controller (not shown), selects only a predetermined area of the digital video signal outputted from the deinterlacer 120, scales the predetermined area, and outputs it to the PDP panel 140. Accordingly, since the image displayer using the scaler 130 displays only the predetermined area of the digital video signal

through the PDP panel 140, it can be adopted in a multi-screen system (e.g. multi-vision system) constructed of a plurality of image displayers.

The control unit 160 controls the scaler 130 in response to control signals sel1 to sel4 generated from the external device such as the remote controller (not shown). Also, the control unit 160 controls the OSD unit 150 in response to the control signals sel1 to sel4 to display a predetermined text and a predetermined menu on the PDP panel 140. In here, the control signals are to select any one of 2 x 2, 4 x 4, and 8 x 8 multi-screen systems and select a reproducing area in the selected system.

The OSD unit 150 has a font and a menu stored therein, for being displayed on the PDP panel 140, and is controlled by the control unit 160 to display the font and the menu on the PDP panel 140.

Preferably, the scaler 130 includes a scaling unit 131, a frame buffer 132, a frame buffer control unit 133, a set value storing unit 134. Next, the scaler 130 will be described below with reference to Figs. 3a and 3b.

The scaling unit 131 enlarges the digital video signal output from the deinterlacer 120 in accordance with the resolution of the PDP panel 140. At this time, prior to enlarging the input digital video signal, the scaling unit 131 sends it to the frame buffer 132 to thus delay it for a predetermined delay time. After that, the scaling unit 131 receives the digital video signal back from the frame buffer 132 and enlarges it.

The frame buffer 132 holds the digital video signal supplied from the scaling unit 131 for the predetermined delay time and outputs it to the scaling unit 131. Meanwhile, the set value storing unit 134 is controlled by the control unit 160 in response to the control signal to output one of pre-stored set values to the frame buffer control unit 133. The set value storing unit 134 stores the data about the reproducing area of the image displayer constructing the multi-screen system corresponding to the control signal, and also the data about the corresponding screen size. For example, when the PDP panel 140 of the image displayer is positioned at the position no. 1 of the multi-screen system as shown in Fig. 3a, the scaler 130 selects one of the digital video signals supplied thereto corresponding the position no. 1 and reproduces the selected digital video signal through the PDP panel 140 in full-screen. The scaler 130 selects and scales an area "b" of the digital video signal "a" as shown in Fig. 3b, and then displays it on the PDP panel 140. Accordingly, the set value storing unit 134 transmits information to the frame buffer control unit 133, informing that the multi-screen

system is 4 x 4 system and the digital video signal is displayed at the position no. 1 of the multi-screen system. In response to the received information, the frame buffer control unit 133 controls the frame buffer 132 to transmit only 1/4 of the digital video signal stored in the frame buffer 132 to the scaling unit 131. Likewise, in case of the 8 x 8 multi-screen system, the area "b" corresponds to 1/8 of the video signal stored in the frame buffer 132.

Fig. 4 is a block diagram according to the second embodiment of the present invention.

The image displayer as shown in Fig 4 includes a video decoder 210, a deinterlacer 220, a video signal selecting unit 230, a frame buffer 240, a scaler 250, and a PDP panel 260.

In regard to the elements identical to those of the third embodiment, description will be omitted.

The video signal selecting unit 230 selects the digital video signals outputted from the deinterlacer 220 based on a horizontal sync signal Hsync and a vertical sync signal Vsync.

The frame buffer 240 integrates the digital video signals selected by the video signal selecting unit 230 based on the horizontal sync signal Hsync and the vertical sync signal Vsync into a single digital video signal.

The scaler 250 enlarges the digital video signal stored in the frame buffer 240 according to the resolution of the PDP panel 260 and outputs it to the PDP panel 260.

Preferably, the video signal selecting unit 230 has a first selecting unit 230a and a second selecting unit 230b.

The first selecting unit 230a selects a digital video signal added to the horizontal sync HSYNC. For example, if a digital video signal corresponding to 720 pixels is located between the horizontal signals and the image displayer is positioned at the position no. 1 of 4 x 4 multi-screen system (Refer to Fig. 3a), the image displayer requires only 180 pixels of 720 pixels of the digital video signal located between the horizontal sync signals Hsync. That is, the first selecting unit 230a selects only the 180 pixels of a front area of the digital video signal added to the horizontal sync signal Hsync.

The second selecting unit 230b selects a digital video signal added to the vertical sync signal Vsync. For example, if a single video frame is comprised of 720 x 480 lines and the image displayer is positioned at the position no. 1 of 4 x 4 multi-screen system, the image displayer selects 120 of 480 vertical sync signals based on the initial vertical sync signal Vsync.

Preferably, the first selecting unit 230a has a first initial value storing unit 231a, a first multiplexer 1MUX 232a, a first counter 233a, and a first exclusive OR gate 234a, which will be explained with reference to FIG. 5A.

When the image displayer is adopted in the multi-screen system, the first initial value
5 storing unit 231a stores set values according to an aspect ratio required for use in the multi-screen system. The first multiplexer 1MUX 232a selects one of the set values stored in the first value storing unit 231a in response to a control signal (select 1) generated from an external device such as a remote controller, and outputs the set value to the first counter 233a. In response to the set value output from the first multiplexer 1 MUX 232a, the first counter
10 233a outputs a pulse of a predetermined width. In here, the set value contains information about the time the first counter 233a starting counting a reference clock CLK and finishes the counting. Illustrated by (b) of Fig. 5a is a pulse that is outputted from the first counter 233a when the image displayer displays the position no. 1 area of the 4 x 4 multi-screen system. As shown in Fig. 5a, the first counter 233a counts the reference clock CLK by N times
15 according to the set value inputted from the first multiplexer 1MUX 232a, and then outputs the "high" logic pulse. Consequently, the exclusive OR gate 234a supplied with output pulses of the deinterlacer 220 and the first counter 233a performs a masking with respect to the digital video signal as shown in (a) of Fig. 5a and outputs the pulse as shown in (c) of Fig. 5b to the frame buffer 240.

20 Fig. 5b shows the pulse outputted from the first counter 233a when the image displayer is employed in the 2 x 2 multi-screen system. As shown in Fig. 5b, the first counter 233a performs a masking with respect to 1/2 of a rear portion of the digital video signal, and supplies the pulse as shown in (c) of Fig. 5b to the exclusive OR gate 234a. Fig. 5C shows the pulse outputted from the first counter 233a when the image displayer is not
25 adopted in the multi-screen system. In this case, the first counter 233a outputs the "low" logic pulse so that the entire digital video signal is displayed on the PDP panel 260.

Preferably, the second selecting unit 230b has a second initial value storing unit 231b, a second multiplexer 2MUX 232b, and the second counter 233b.

The second initial value storing unit 231b has counter values according to a display
30 area required when the image displayer is adopted in the multi-screen system. The second multiplexer 2MUX 232b supplies to the second counter 232b one of set values stored in the second initial value storing unit 231b in response to a control signal (select 2) generated from

the external device such as the remote controller (not shown). In response to the set value supplied from the second multiplexer 2MUX 232b, the second counter 233b selects the vertical sync signal and a predetermined of the digital video signal added to the vertical sync signal. In here, the set value, which is supplied to the second counter 233b from the second
5 initial value storing unit 231b through the second multiplexer 2MUX 232b, contains information about the time the second counter 233b starts and finishes counting. The second exclusive OR gate 234b performs masking with respect to the digital video signal outputted from the deinterlacer 220, using the pulse outputted from the second counter 233b, and outputs the digital video signal to the frame buffer 240.

10 Fig. 6 is an example of an OSD menu for setting the image displayer.

As shown in Fig. 6, the OSD menu has a channel setting menu 310, an image quality setting menu 320, a sound menu 330, and other menus 340. The multi-screen function is included in other menus 340. When other menus 340 are selected through a setting key attached on a remote controller (not shown) or the image displayer, menus for multi-vision
15 and time adjustment are displayed. Next, with the selection of the multi-vision, a sub-menu window 312 is popped-out, asking the selection of the multi-screen system. When the 2 x 2 multi-screen system is selected, a menu is displayed, asking which position the image displayer is placed. As described above, the image displayer does not require an expensive signal separator because the multi-screen function can be performed through the menus, and
20 can avoid the possible problem which is caused when the number of the image displayers does not correspond to the output ports of the signal separator.

[Effect of the invention]

As described above, in the N x N multi-screen system, the image displayer of the present invention does not require the separate signal separator and is not limited in number.
25 Also, when the image displayer is not in use for the multi-screen system, it can be used as a general image displayer for receiving broadcasting signals.

Although a few preferred embodiments of the present invention has been described for illustrative purposes, those skilled in the art will appreciate that various modifications, additions and substitutions are possible, without departing from the scope and spirit of the
30 invention as disclosed in the accompanying claims.

[What is claimed is]

[Claim 1]

An image displayer of a multi-screen system, which is comprised of at least two image displayers, each image displayer comprising:

a screen;

a video decoder for performing an analog-to-digital conversion with respect to a video input signal; and

a scaler for selecting a video signal corresponding to a predetermined area of the screen from video signals outputted from the video decoder by an externally transmitted control signal, and enlarging the selected video signal according to a size of the screen.

[Claim 2]

The image displayer of claim 1, wherein the scaler comprises:

a signal selecting unit for selecting a predetermined area of the video signal outputted from the video decoder; and

a scaling unit for enlarging the video signal selected by the signal selecting unit according to the size of the screen.

[Claim 3]

The image displayer of claim 2, wherein the signal selecting unit comprises:

a frame buffer for being inputted with the video signal outputted from the video decoder and storing the video signal for a predetermined time, and then outputting the video signal to the scaling unit;

a set value storing unit for storing a set value for the multi-screen function; and

a frame buffer control unit for selecting a predetermined area of the video signal of the video decoder stored in the frame buffer in response to one of the set values pre-set by the set value storing unit.

[Claim 4]

The image displayer of claim 3, further comprising a control unit for selecting one of the plurality of set values stored in the set value storing unit in response to an externally transmitted control signal.

[Claim 5]

The image displayer of claim 4, further comprising an OSD unit for displaying a predetermined font on the screen according to the control signal supplied from the control unit, and controlling the multi-screen function on an OSD window.

[Claim 6]

The image displayer of claim 5, wherein the externally transmitted control signal is the one generated by a setting key attached to a remote controller and the image displayer.

[Claim 7]

An image displayer comprising:

5 a video decoder for performing an analog-to-digital conversion with respect to an video input signal;

a video signal selecting unit for selecting a video signal outputted from the video decoder to display in a predetermined area of a screen in response to an externally transmitted control signal;

10 a frame buffer for receiving the video signal selected by the video signal selecting unit and re-ordering the video signal by the order of input; and

a scaler for scaling the video signal re-arranged by the frame buffer.

[Claim 8]

The image displayer of claim 7, wherein the video signal selecting unit comprises:

15 a first selecting unit for selecting a predetermined area of a video signal added to a horizontal sync signal of the video input signal converted from analog to digital by the video decoder; and

a second selecting unit for selecting a predetermined area of a video signal added to a vertical sync signal of the video input signal converted from analog to digital by the video
20 decoder.

[Claim 9]

The image displayer of claim 8, wherein the first selecting unit comprises:

a first initial value storing unit for storing a plurality of initial values for the selection of the predetermined area of the video signal outputted from the video decoder and added to
25 the horizontal sync value;

a first multiplexer for selecting one of the initial values stored in the first initial value storing unit in response to the externally transmitted control signal;

a first counter for generating a pulse of a predetermined period based on the initial value selected by the first multiplexer; and

30 a first exclusive OR gate for performing a masking with respect to the video signal outputted from the video decoder using the pulse outputted from the first counter and outputting only a desired area of the video signal.

[Claim 10]

The image displayer of claim 8, wherein the second selecting unit comprises:

- a second initial value storing unit for storing a plurality of initial values for the selection of the predetermined area of the video signal outputted from the video decoder and
5 added to the vertical sync signal;
- a second multiplexer for selecting any one value of the initial values stored in the second initial value storing unit in response to the control signal from the external device;
- a second counter for generating a pulse of a predetermined period according to the initial value selected by the second multiplexer; and
10 a second exclusive OR gate for performing a masking with respect to the video signal outputted from the video decoder, using the pulse output from the second counter, thereby outputting only a desired area of the vide signal.

[Claim 11]

- The image displayer of claim 7, further comprising an OSD unit for displaying a
15 predetermined font on the screen in response to the externally transmitted control signal so that the multi-screen function can be controlled on the OSD.